

Алматы (7273)495-231
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +7(7172)727-132

Киргизия +996(312)96-26-47

<https://luve.nt-rt.ru> || uev@nt-rt.ru

Конденсаторы EHV Ø 900 - EAV Ø 800 - 900

176 - 1320 kW

EHV Ø 900 - EAV Ø 800 - 900

Condensatori ventilati
Air cooled condensers



Modello	Type	EHV90F (2.1 mm)			364		366				368		370				372			
Potenza	Capacity	kW (ΔT 15K)				396	324	440	340			594	486	660	510			792	648	
Portata d'aria	Air quantity	m³/h				106000	76000	98000	68400			159000	114000	147000	102200			212000	152000	
Assorbimento motori	6P Ø900	W				13000	8000	13000	8000			19500	12000	19500	12000			26000	16000	
Motor power consumption		A				24,0	14,0	24,0	14,0			36,0	21,0	36,0	21,0			48,0	28,0	
Livello pressione sonora	Sound pressure level	dB (A) (total)				62	55	62	55			64	57	64	57			65	58	
Attacchi	Connections	Ø mm				2 x 54/42		2 x 54/42				2 x 76/54		2 x 76/54				2 x 76/54		
Circuiti	Circuits	n°				2 x 44		2 x 44				2 x 66		2 x 88				2 x 66		
Modello	Type	EAV9N (2.1 mm)			6221		6222				6231		6232				6241			
Potenza	Capacity	kW (ΔT 15K)				364	304	404	316			546	456	606	474			728	608	
Portata d'aria	Air quantity	m³/h				94000	70400	88000	64000			141000	105600	132000	96000			188000	140800	
Assorbimento motori	6P Ø900	W				9600	6360	9600	6360			14400	9540	14400	9540			19200	12720	
Motor power consumption		A				20,8	12	20,8	12			31,2	18	31,2	18			41,6	24	
Livello pressione sonora	Sound pressure level	dB (A) (total)				58	51	58	51			60	53	60	53			61	54	
Attacchi	Connections	Ø mm				2 x 54/42		2 x 54/42				2 x 76/54		2x76/54				2x76/54		
Circuiti	Circuits	n°				66		88				132		176				132		
Modello	Type	EAV8S (2.1 mm)			7221		7222				7231		7232				7241			
Potenza	Capacity	kW (ΔT 15K)				316	268	348	276			474	402	522	414			632	536	
Portata d'aria	Air quantity	m³/h				77200	58000	72800	55200			115800	87000	109200	82800			154400	116000	
Assorbimento motori	6P Ø800	W				6800	4600	6800	4600			10200	6900	10200	6900			13600	9200	
Motor power consumption		A				14,8	8,4	14,8	8,4			22,2	12,6	22,2	12,6			29,6	16,8	
Livello pressione sonora	Sound pressure level	dB (A) (total)				52	45	52	45			54	47	54	47			55	48	
Attacchi	Connections	Ø mm				2 x 54/42		2 x 54/42				2 x 76/54		2x76/54				2x76/54		
Circuiti	Circuits	n°				66		88				132		176				132		
Modello	Type	EAV9X (2.1 mm)			1220		1221		1222		1230		1231		1232		1240		1241	
Potenza	Capacity	kW (ΔT 15K)			240	200	280	220	284	220	360	300	420	330	426	330	480	400	560	440
Portata d'aria	Air quantity	m³/h			65600	49200	60800	44400	56400	40400	98400	73800	91200	66600	84600	60600	131200	98400	121600	88800
Assorbimento motori	8P Ø900	W			3440	2120	3440	2120	3440	2120	5160	3180	5160	3180	5160	3180	6880	4240	6880	4240
Motor power consumption		A			8,8	4,6	8,8	4,6	8,8	4,6	13,2	6,9	13,2	6,9	13,2	6,9	17,6	9,2	17,6	9,2
Livello pressione sonora	Sound pressure level	dB (A) (total)			47	40	47	40	47	40	49	42	49	42	49	42	50	43	50	43
Attacchi	Connections	Ø mm			2x42/35		2x54/42		2x54/42		2x54/42		2x76/54		2x76/54		2x54/42		2x76/54	
Circuiti	Circuits	n°			44		66		88		88		132		176		88		132	
Modello	Type	EAV8T (2.1 mm)			8220		8221		8222		8230		8231		8232		8240		8241	
Potenza	Capacity	kW (ΔT 15K)			220	192	256	212	268	212	330	288	384	318	402	318	440	384	512	424
Portata d'aria	Air quantity	m³/h			60800	47600	56800	43600	52000	39200	91200	71400	85200	65400	78000	58800	121600	95200	113600	87200
Assorbimento motori	8P Ø800	W			3280	2080	3280	2080	3280	2080	4920	3120	4920	3120	4920	3120	6560	4160	6560	4160
Motor power consumption		A			9,2	4,4	9,2	4,4	9,2	4,4	13,8	6,6	13,8	6,6	13,8	6,6	18,4	8,8	18,4	8,8
Livello pressione sonora	Sound pressure level	dB (A) (total)			45	40	45	40	45	40	47	42	47	42	47	42	48	43	48	43
Attacchi	Connections	Ø mm			2x42/35		2x54/42		2x54/42		2x54/42		2x76/54		2x76/54		2x54/42		2x76/54	
Circuiti	Circuits	n°			44		66		88		88		132		176		88		132	
Modello	Type	EAV9U (2.1 mm)			5220		5221				5230		5231				5240		5241	
Potenza	Capacity	kW (ΔT 15K)			176	148	192	152			264	222	288	228			352	296	384	304
Portata d'aria	Air quantity	m³/h			40800	32000	37600	28800			61200	48000	56400	43200			81600	64000	75200	57600
Assorbimento motori	12P Ø900	W			1100	700	1100	700			1650	1050	1650	1050			2200	1400	2200	1400
Motor power consumption		A			3,2	1,6	3,2	1,6			4,8	2,4	4,8	2,4			6,4	3,2	6,4	3,2
Livello pressione sonora	Sound pressure level	dB (A) (total)			36	30	36	30			38	32	38	32			39	33	39	33
Attacchi	Connections	Ø mm			2x42/35		2x54/42				2x54/42		2x54/42				2x54/42		2x76/54	
Circuiti	Circuits	n°			44		66				88		66				88		132	

DATI COMUNI / COMMON DATA

Elettroventilatori		Ø 800-900 mm x n°	4 		4 		4 		6 		6 		6 		8 		8	
Fans		Collegamento	Connection		△		△		△		△		△		△		△	
Superficie esterna	External surface	m²	350		525,2		700,4		525		787,8		1050,6		700		1050,4	
Superficie interna	Internal surface	m²	46,0		69,3		91,5		69,0		103,9		137,3		92,0		138,5	
Volume circuito	Circuit volume	dm³	58		87		114		87		134		173		114		174	
Peso	Weight	kg (H)	645		723		794		920		1047		1153		1200		1358	



■ Attacchi lati opposti
■ Connections opposite sides



374		376		378		380		382	
880	680	990	810	1100	850	1188	972	1320	1020
196000	136800	265000	190000	245000	171000	318000	228000	294000	205200
26000	16000	32500	20000	32500	20000	39000	24000	39000	24000
48,0	28,0	60,0	35,0	60,0	35,0	72,0	42,00	72,0	42,0
65	58	66	59	66	59	67	60	67	60
2 x 76/54		2 x 89/64		2 x 89/64		2 x 89/64		2 x 89/64	
2 x 88		2 x 132		2 x 176		2 x 132		2 x 176	
6242		6251		6252		6261		6262	
808	632	910	760	1010	790	1092	912	1212	948
176000	128000	235000	176000	220000	160000	282000	211200	264000	192000
19200	12720	24000	15900	24000	15900	28800	19080	28800	19080
41,6	24	52	30	52	30	62,4	36	62,4	36
61	54	62	55	62	55	63	56	63	56
2x76/54		2x76/54		2x76/54		2x89/64		2x89/64	
176		132		176		264		352	
7242		7251		7252		7261		7262	
696	552	790	670	870	690	948	804	1044	828
145600	110400	193000	145000	182000	138000	231600	174000	218400	165600
13600	9200	17000	11500	17000	11500	20400	13800	20400	13800
29,6	16,8	37,0	21,0	37,0	21,0	44,4	25,2	44,4	25,2
55	48	56	49	56	49	57	50	57	50
2x76/54		2x76/54		2x76/54		2x89/64		2x89/64	
176		132		176		264		352	
1242		1250		1251		1252		1260	
568	440	600	500	700	550	710	550	720	600
112800	80800	164000	123000	152000	111000	141000	101000	196800	147600
6880	4240	8600	5300	8600	5300	8600	5300	10320	6360
17,6	9,2	22	11,5	22	11,5	22	11,5	26,4	13,8
50	43	51	44	51	44	51	44	52	45
2x76/54		2x76/54		2x76/54		2x76/54		2x89/64	
176		176		132		176		176	
8242		8250		8251		8252		8260	
536	424	550	480	660	530	670	530	660	576
104000	78400	152000	119000	142000	109000	130000	98000	182400	142800
6560	4160	8200	5200	8200	5200	8200	5200	9840	6240
18,4	8,8	23,0	11,0	23,0	11,0	23,0	11,0	27,6	13,2
48	43	49	44	49	44	49	44	50	45
2x76/54		2x76/54		2x76/54		2x76/54		2x89/64	
176		176		132		176		176	
5250		5251		5260		5261			
	440	370	480	380		528	444	576	456
	102000	80000	94000	72000		122400	96000	112800	86400
	2750	1750	2750	1750		3300	2100	3300	2100
	8	4	8	4		9,6	4,8	9,6	4,8
	40	34	40	34		41	35	41	35
	2x54/42		2x76/54			2x76/54		2x76/54	
	88		132			176		132	
8 0000		10 0000		10 0000		10 0000		12 0000	
△	△	△	△	△	△	△	△	△	△
1400,8		875		1313		1751		1050	
183,1		115,0		173,2		228,8		138,0	
226		140		219		285		179	
1497		1490		1684		1862		1797	

Алматы (7273)495-231
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +7(7172)727-132

Киргизия +996(312)96-26-47